

## Primo by Doro 405 Specification

	Main	Sub	Details
<b>Hardware</b>			
1	Platform	MTK6260D	
2	Form	Bar type	
3	SIM	Single SIM	
4	Mode	GSM+GPRS	
5	Frequency	GSM 900/1800M or GSM850/1900 (Duo-band)	
6	Antenna	Interior	
7	LCM	Size	2.2"
		Nature	TFT
		Colors	65K
		Resolution	220*176 pixels
8	Camera	type	VGA
		pixels	0.3M
		Flashlight	yes
9	Micro-SD Card	Yes	support up to 32GB
10	Keypad	Side-key	volume +/-
		Number key	0-9, #, *
		Function keys	dialing, end, up, down, LSK (Menu), RSK (Names), SOS key, M1 M2 M3 direct dialing key
		Keypad backlight	White
		SOS key	Can be defined
11	Keypad LED	6 pcs	
12	USB	Micro-USB, data transfer and charging	
13	Earpiece	3.5mm standard	on the side
14	Flashing port	Micro-usb	use normal cable
15	Speaker	20*14mm	
16	FM	yes	listening FM by plug-in earpiece
17	Bluetooth	Yes	V3.0
18	Torch	soft key	shared with camera flash light
19	Cradle charge	Yes	easy charging
20	Battery	Spec	3.7V, 1,000mAh Lion
		Talking time	more than 5 hrs
		Standby time	10 days
		* Battery life varies from the network signal level	
<b>Software function</b>			
1	Phone book	Storage	200
2	SMS	SMS	50
3	Ringer	Format	MIDI, mp3, amr
4	SOS	Emergency call	5 numbers (Note: define as per needed)
5	Alarm	Yes	5 items
6	MMS	Yes	
8	GPRS	Yes	Class1.2
9	WAP	No	
10	TOP 10	Yes	as Doro samples
11	ICE	Yes	as Doro samples
12	SOS new function	Yes	during normal phone call, SOS can be switched between Speaker Mode on/off
13	Languages	7	German, English, Czech, Spanish, French, Turkish, Hungarian